

Conn./ Plug/Pin	Pin Information	Test Value	Comments
2L.6	Circuit 58d output, "Dimmed Instrument illumination" voltage	Varies from 0.5-12 VDC, depending on setting of dimming value and ambient brightness	Short protected, current decoupled from circuit 58k
2M.1	CAN-Bus (low side). High speed data transfer bus input and output, shares data with radio or COMAND	No reliable test. Check continuity of wiring	Use SDS to test
2M.2	CAN-Bus (high side)	See pin 2M.1	
2N.1	Horn contact signal output	No reliable test	
2N.2	Pin not used		

Pin Information, Part 3