



Vehicle Selection

Audio/Video

Mercedes Benz E320 1998 4DR Sedan

Base system					
Radio Harness » Base system Wire Function	Colour	Notes	Fuse #	Fuse Size	Fuse Location
		Notes	5		Fuse box below right rear
+12V DC Battery(Constant)				25 Amp	seat
Switched Accessory	Black/red/violet	0-	11	15 amp	Front fuse/relay box
Ground	Brown	Ur	black/yellow		
Power Antenna	Blue/white				
Illumination	Gray/blue				
	Disarms with				
Factory Alarm Disarm	unlock wire				
VSS Wire	Green/black				
Left Front +	Green				
Left Front -	Brown/green				
Right Front +	Black				
Right Front - Left Rear +	Brown/black	Ind	adan ar lim	a branches of	f to the other year marker
Left Rear +	Pink Brown/pink			•	f to the other rear speaker. f to the other rear speaker.
		_		·	or limo, branches off to the
Right Rear +	White		er rear spea		i or ilino, branches on to the
Dight Door -	Prown/white	Cha	inges to bro	wn/pink and, i	n sedan or limo, branches of
Right Rear -	Brown/white	to t	the other rea	ar speaker.	
At Speakers » Base system		 	_	T =	I
Wire Function	Colour	Notes	Fuse #	Fuse Size	Fuse Location
Left Front Tweeter +	Green		<u> </u>	er (see notes)	
Left Front Tweeter -	Brown/green		angle speake		
Right Front Tweeter +	Green		angle speake		
Right Front Tweeter - Right Rear Mid +	Brown/green NCA	1110	angle speake	:1	
Right Rear Mid -	NCA				
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t	branching from the				"rear door mirror triangle
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t	branching from the				"rear door mirror triangle
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi	branching from the				"rear door mirror triangle Fuse Location
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function	branching from the the extra rear speak	ers (in the s	edan or limo	o).	Fuse Location Fuse box below right rear
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function +12V DC Battery(Constant)	branching from the the extra rear speak	ers (in the s	Fuse #	Fuse Size	Fuse Location Fuse box below right rear seat
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function +12V DC Battery(Constant)	branching from the the extra rear speak	Notes	Fuse # 5	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function +12V DC Battery(Constant) Switched Accessory	branching from the the extra rear speak	Notes	Fuse #	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function +12V DC Battery(Constant) Switched Accessory Ground	branching from the the extra rear speaks the	Notes	Fuse # 5	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function +12V DC Battery(Constant) Switched Accessory Ground Power Antenna	branching from the the extra rear speak the extra r	Notes Or	Fuse # 5 11 black/yellow	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function +12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output)	branching from the the extra rear speak the extra r	Notes Or	Fuse # 5 11 black/yellow	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function +12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output)	branching from the the extra rear speak the extra r	Notes Or	Fuse # 5 11 black/yellow	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function +12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination	branching from the the extra rear speaks the	Notes Or	Fuse # 5 11 black/yellow	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the with amplifier Radio Harness With amplifier H12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination Factory Alarm Disarm	branching from the the extra rear speak the extra rear speak the extra rear speak to the extra rear speak the extr	Notes Or	Fuse # 5 11 black/yellow	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for t With amplifier Radio Harness » With amplifi Wire Function +12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination Factory Alarm Disarm VSS Wire	branching from the the extra rear speak the extra rear speak the extra rear speak to the extra rear speak to the extra rear speak the e	Notes Or	Fuse # 5 11 black/yellow	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the with amplifier Radio Harness With amplifier Radio Harness With amplifier H12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination Factory Alarm Disarm VSS Wire Amplifier Output With an	branching from the the extra rear speak the extra rear speak the extra rear speak to the extra rear speak to the extra rear speak the e	Notes Or	Fuse # 5 11 black/yellow	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the with amplifier Radio Harness With amplifier Radio Harness With amplifier H12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination Factory Alarm Disarm VSS Wire Amplifier Output With an Wire Function	branching from the the extra rear speak the extra rear speak the extra rear speak to the extra rear sp	Notes Or Pin wel	Fuse # 5 11 black/yellow A-5 on radii, in trunk)	Fuse Size 25 Amp 15 Amp to to pin 8 of ar	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left whee
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the with amplifier Radio Harness "With amplifier Radio Harness "With amplifier Function +12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination Factory Alarm Disarm VSS Wire Amplifier Output "With an Wire Function 12V DC Battery	branching from the the extra rear speak the extra r	Notes Or Pin wel	Fuse # 5 11 black/yellow A-5 on radii	Fuse Size 25 Amp 15 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box Implifier (located at left whee
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the with amplifier Radio Harness With amplifier Radio Harness With amplifier Fraction Fractory Alarm Disarm WSS Wire Amplifier Output With amplifier Output 12V DC Battery Wire Function Fractory Alarm Disarm WSS Wire Amplifier Output With amplifier Output 12V DC Battery Remote Turn On (input)	branching from the the extra rear speaks the	Notes Or Pin wel	Fuse # 5 11 black/yellow A-5 on radii I, in trunk) Fuse # 16	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left whee
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the tweeters in our source. There is no colour available for the tweeters in our source. With amplifier Radio Harness With amplifier Radio Harness With amplifier Wire Function +12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination Factory Alarm Disarm VSS Wire Amplifier Output With an Wire Function 12V DC Battery Remote Turn On (input) Left Front Mid +	branching from the the extra rear speak for the extra sp	Notes Pin wel Notes Cha	Fuse # 5 11 black/yellow A-5 on radiil, in trunk) Fuse # 16	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp wn/green	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left whee
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the with amplifier Radio Harness With amplifier Radio Harness With amplifier Radio Harness With amplifier Wire Function +12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination Factory Alarm Disarm VSS Wire Amplifier Output With an Wire Function 12V DC Battery Remote Turn On (input) Left Front Mid + Left Front Mid -	branching from the the extra rear speak. Colour Red/white Black/red/violet Brown Blue/white Blue/white Gray/blue Disarms with unlock wire Green/black pilifier Colour Red/blue/white Blue/white	Notes Pin wel Notes Cha	Fuse # 5 11 black/yellow A-5 on radii I, in trunk) Fuse # 16	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp wn/green	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left whee
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. With amplifier Radio Harness	branching from the the extra rear speak the extra speak the	Notes Pin wel Notes Cha	Fuse # 5 11 black/yellow A-5 on radiil, in trunk) Fuse # 16	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp wn/green	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left whee
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. With amplifier Radio Harness "With amplifier Function H12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination Factory Alarm Disarm VSS Wire Amplifier Output "With an Wire Function 12V DC Battery Remote Turn On (input) Left Front Mid + Left Front Mid + Right Front Mid -	branching from the the extra rear speak the extra spea	Notes Pin wel Notes Cha	Fuse # 5 11 black/yellow A-5 on radii I, in trunk) Fuse # 16 anges to broanges to green	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left whee
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. With amplifier Radio Harness "With amplifier Radio Harness "With amplifier Function +12V DC Battery(Constant) Switched Accessory Ground Power Antenna Remote Turn On(output) Illumination Factory Alarm Disarm VSS Wire Amplifier Output "With an Wire Function 12V DC Battery Remote Turn On (input) Left Front Mid + Left Front Mid - Right Front Mid - Left Rear Mid +	branching from the the extra rear speak the extra rear speak the extra rear speak to the extra rear sp	Notes Pin wel Notes Cha	Fuse # 5 11 black/yellow A-5 on radii I, in trunk) Fuse # 16 anges to broanges to green	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left whee
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. With amplifier Radio Harness ** With amplifier Radio Harness ** With amplifier Wire Function Factory Alarm Disarm VSS Wire Amplifier Output With an Wire Function 12V DC Battery Remote Turn On (input) Left Front Mid + Left Front Mid - Right Front Mid - Right Front Mid - Left Rear Mid + Left Rear Mid + Left Rear Mid -	branching from the the extra rear speak the extra spea	Notes Pin wel Notes Cha	Fuse # 5 11 black/yellow A-5 on radial, in trunk) Fuse # 16 anges to broanges to gre or speaker or speaker	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp wn/green en	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left wheel Fuse Location Fuse box below right rear seat
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. With amplifier Radio Harness ** With amplifier Radio Harness ** With amplifier Radio Harness ** With amplifier Wire Function Factory Alarm Disarm VSS Wire Amplifier Output ** With an Wire Function 12V DC Battery Remote Turn On (input) Left Front Mid + Left Front Mid + Right Front Mid - Left Rear Mid + Left Rear Mid - Right Rear Mid -	branching from the the extra rear speak the extra rear speak the extra rear speak to the extra speak t	Notes Pin wel Notes Chacker	Fuse # 5 11 black/yellow A-5 on radial, in trunk) Fuse # 16 anges to broanges to green or speaker or speaker anges to broanges to b	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp wn/green en	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left whee location Fuse box below right rear seat
Notes Front tweeters: these speakers, speaker" in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. There is no colour available for the speaker in our source. With amplifier Radio Harness ** With amplifier Radio Harness ** With amplifier Wire Function Factory Alarm Disarm VSS Wire Amplifier Output ** With an Wire Function 12V DC Battery Remote Turn On (input) Left Front Mid + Left Front Mid - Right Front Mid - Left Rear Mid + Left Rear Mid + Left Rear Mid + Right Rear Mid + Right Rear Mid + Right Rear Mid -	branching from the the extra rear speak the extra rear speak the extra rear speak to the extra speak t	Notes Pin wel Notes Cha Cha Cha Cha Cha To	Fuse # 5 11 black/yellow A-5 on radii I, in trunk) Fuse # 16 anges to broanges to gree or speaker anges to broanging to pir pin 1 of bas	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp wn/green en wn/pink; this is the dis module (stati	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left whee location Fuse box below right rear seat
	branching from the the extra rear speak the extra rear speak the extra rear speak to the extra speak t	Notes Pin wel Notes Cha Cha Cha Cha To spe	Fuse # 5 11 black/yellow A-5 on radii I, in trunk) Fuse # 16 anges to broanges to gree or speaker or speaker anges to broanges to great the broanges to broanges	Fuse Size 25 Amp 15 Amp to to pin 8 of ar Fuse Size 25 Amp wn/green en wn/pink; this is the distribution of the pink of of t	Fuse Location Fuse box below right rear seat Front fuse/relay box Inplifier (located at left wheel Fuse Location Fuse box below right rear seat In the box below right rear seat In the box below right rear seat

Subwoofer 2 +	Blue	To pin 3 of bass module (station wagon) or to right rear speaker (sedan & limo)			
Subwoofer 2 -	Brown/blue	To pin 4 of bass module (station wagon) or to right rear speaker (sedan & limo)			
Notes					
Colours directly at the speaker end are not available.					

Legend: * iC info * Δ iC info awaiting approval

Speakers		
Location	Size	Depth
Front Doors	5 1/4 "	
Rear Doors	5 1/4 "	

NOTE: The information on this sheet is provided to you on an as is basis with no representation or warranty of accuracy whatsoever. It is the sole responsibility of the installer to check and verify any circuit before connecting to it. Only a computer safe logic probe or digital multimeter should be used.

Autoland and/or any associated or unassociated individual or corporation who furnishes this document and/or software assumes absolutely no liability or responsibility whatsoever pertaining to the accuracy or currency of the information supplied.

The installation in each and every case is the sole responsibility of the installer performing the work and Autoland and/or any associated or unassociated individual or corporation assumes no liability or responsibility whatsoever resulting from any type of installation, whether performed properly, improperly, or in any other way.

The information supplied is a guide only.

© 2013 Installogy.com | 634992872300243758